

TECHNICAL SPECIFICATIONS

TX230 VAC 1kVA

GENERAL DATA

Output power	0,9 KW
Topology	True online double conversion

INPUT DATA

Voltage Range	Transfer voltage - low	160VAC/140VAC/120VAC/110VAC \pm 5% \circ 80VAC/70VAC/60VAC/55VAC \pm 5% (base % load: 100% - 80% / 80% - 70% / 70% - 60% / 60% - 0)
	Return voltage low	175VAC/155VAC/135VAC/125VAC \pm 5% \circ 87VAC/77VAC/67VAC/62VAC \pm 5%
	Transfer voltage high	300 VAC \pm 5% \circ 150 VAC \pm 5%
	Return voltage - high	290 VAC \pm 5% \circ 145 VAC \pm 5%
Frequency range	40Hz - 70Hz	
Power factor	\geq 0.99 @ full load	
THDi	\leq 5% @ 205-245VAC \circ 100-130VAC THDU 1.6% @ input and full linear load with charged batteries	

OUTPUT DATA

Voltage	200/208/220/230/240 \circ 100/110/115/120/127 VAC	
AC voltage regulation	\pm 1% (Battery mode)	
Frequency range (Gamma synchronism)	47 - 53Hz \circ 57 - 63Hz	
Frequency range (Battery mode)	50Hz \pm 0.1Hz \circ 60Hz \pm 0.1Hz	
Peak current value	3:1	
Harmonic distortion	\leq 2% THD linear load \leq 4% THD non-linear load	
Transfer Time	AC battery mode	0ms
	Inverter to Bypass	4 ms (Typical)
	Wave shape (Battery mode)	<10ms
Wave shape (Battery mode)	Sinusoidal	

EFFICIENCY

In AC mode	90%
In battery mode	86%

BATTERIES

Type of battery	12V/7Ah
Quantity	3
Recharging time	4 hours per load at 90% of capacity (Typical)
Charging load	1.5 A
Load voltage	41 VDC \pm 1%

TECHNICAL SPECIFICATIONS

TX230 VAC 1kVA

MECHANICAL DATA

D x W x H	397 x 145 x 220 mm
Net weight (kg)	12.5
Color	Black

ENVIRONMENTAL PARAMETERS

Operating temperature	0-40 °C
Relative humidity	20-95% RH @ 0-40°C (without condensation)
Noise level	< 50 dBA @ 1 meter

INDICATORS

Status	Load level, Battery level, Battery mode, AC mode, Bypass mode, Failure
--------	--

AUDIBLE ALARM

Battery operation mode	Beeps every 4 seconds
Low battery	Sound every 2 seconds
Overload	Sound every second
Failure	Sound every 2 seconds

MANAGEMENT

Smart RS232 o USB	Supports Windows 2000/2003/XP/Vista/2008 ,7.8, Linux, Unix and MAC
SNMP (opcional)	Power management from SNMP manager and web browser

